



| | |
|-------------------------|---------------------|
| Symbol: | AX-595 |
| Skupina výrobků: | Digital Multimeters |

Parametry výrobku

| | |
|---------------------------------------|---|
| Type of meter: | digital multimeter |
| Interface: | USB |
| Measurement: | AC current, AC voltage, capacitance, DC current, DC voltage, frequency, relative, resistance, temperature |
| Kind of display used: | LCD |
| Display parameters: | (5999) |
| Sampling: | 3x/s |
| DC voltage measuring range: | 0.1...600mV, 6V, 60V, 600V, 1kV |
| DC voltage measuring accuracy: | $\pm(0.5\% + 4 \text{ digit})$ |
| AC voltage measuring range: | 1mV...6V, 60V, 600V, 750V |
| AC voltage measuring accuracy: | $\pm(1\% + 6 \text{ digit})$ |
| DC current measuring range: | 10 μ A...60mA, 600mA, 6A, 10A |
| DC current measuring accuracy: | $\pm(1\% + 10 \text{ digit})$ |

Karta výrobku AX-595

| | |
|--|---|
| AC current measuring range: | 10 μ A...60mA, 600mA, 6A, 10A |
| AC current measuring accuracy: | $\pm(1.5\% + 10 \text{ digit})$ |
| Resistance measuring range: | 100m Ω ...600 Ω , 6k Ω , 60k Ω , 600k Ω , 6M Ω , 60M Ω |
| Capacitance measuring range: | 10pF...40nF, 400nF, 4 μ F, 40 μ F, 200 μ F |
| Capacitance measuring accuracy: | $\pm(3.5\% + 8 \text{ digit})$ |
| Frequency measuring range: | 1mHz...10Hz, 100Hz, 1kHz, 10kHz, 100kHz, 1MHz, 20MHz |
| Frequency measuring accuracy: | $\pm(0.3\% + 2 \text{ digit})$ |
| Temperature measuring range: | -20...1000 $^{\circ}$ C |
| Resistance measuring accuracy: | $\pm(0.8\% + 4 \text{ digit})$ |
| Diode test: | 1mA @3V |
| Continuity test: | acoustic indication, <30 Ω |
| Weight with battery: | 410g |
| Power supply: | battery LR03 AAA 1,5V x2 |
| Standard equipment: | K-type temperature probe, test leads, USB cable |

| | |
|---------------------------------------|---|
| Optional equipment: | test leads AX-TL-4B1-B, test leads AX-TL-4B1-BL, testleads AX-TL-4B1-R, test leads AX-TL-BNC-4BP2, test leads AX-TLP-001, test leads AX-TLP-001T, test leads AX-TLP-002, test leads AX-TLP-003, test leads AX-TLS-001B, testleads AX-TLS-002B, test leads AX-TLS-003A, test leads AX-TLS-004A, test leads AX-TLS-005A, test leads AX-TLS-007S, test leads PPOM-14, test tweezers AX-TLP-TW-01 |
| Conform to the norm: | CAT III 1000V, CAT IV 600V, EN 61010 |
| Related items: | 5790D, 5793D, 5794D, 5795D, 5797D, BKP60, EX871515, EX881602, EX881603, EX881605, PKT-PTA, PKT-PTF-10, PKT-PTF-20, PKT-PTF-25, PKT-PTF-30, PKT-PTF-40, PKT-PTF-50, PKT-PTF-55, PKT-PTF-56, PKT-PTF-60, SE027, SE028, SE029, SE030, SE031, SE059, SE060, SE061, SE062, SE001, SE002, SE003, SE004, SE000, TESTO-06020393, TESTO-06020645, TESTO-06024592, TESTO-06024892, TESTO-06280020, TESTO-06281292, TESTO-06287533, TP200, TP400, TP870, TP873, TP873-5M, TP882, TP-111, TP-112, TP-02, TP-03, TP-04, TP-06, TP-08, TP-09, TPK-59, TPK-62, UTT10K, UTT12 |
| Dimensions (W x H x D): | 91x185x49mm |
| Measuring instrument features: | auto and manual ranging, automatic power-off, HOLD function, low battery indicator, MIN/MAX function |
| Software: | included |
| Bargraph: | yes |

Doplňková informace

| | |
|-------------------------|-----------|
| Hmotnost brutto: | 0.8515 kg |
|-------------------------|-----------|